



DISPLAYS accessories: Bidirectional CAN-Converter

MOTOMETER

powered by solutions

Electrical specifications

Voltage range: 8 - 32V
Test voltage: 27V
Overvoltage: 36V / 1h at 40°C operation temperature
Nominal voltage: 12V / 24V

Stand-by current (cl. 15 off): <10µA
Operating current: typ. 10mA

Input CAN-interface


Baud rate: 100kBaud - 1MBaud
Communication protocol: Can 2.0B, 29 bit, J1939

Output

Number of inputs/outputs: 4

Mechanical specifications

Storage temperature: 100°C / 2h
Operating temperature: -40°C - 85°C
Protection type: IP54
Drop test: In case of drop > 1m,
do not use this part
Resistance against media: t.b.d.
Place of installation: variable
Material of housing: PA6 GF
Material of socket: PA6 GF
Material of pins: CuZn 37F37



Pin assignment

1	output / input 1
2	cl. 15 (ignition)
3	output / input 2
4	output / input 3
5	cl. 30 (+Ub)
6	cl. 31 (GND)
7	CAN high
8	output / input 4
9	CAN low

IVEKA GmbH

Talweg 8 | 75417 Mühlacker-Lomersheim/Germany

Phone +49 7041 9695-0 | Fax +49 7041 9695-55 | E-Mail info@iveka.de

www.IVEKA.de



DISPLAYS accessories: Bidirectional CAN-Converter

MOTOMETER

powered by solutions

Analogue Inputs

configurable, max. 4

- 0 - 120 Ohm
- 0 - 300 Ohm
- 0 - 2 kOhm
- 0 - 30 kOhm
- 0 - 5 Volt
- 0 - 10 Volt
- 4 - 20 mA
- 0 - 20 mA

Frequency inputs: 0 -20 kHz

Analogue Outputs

max. 4

- 0 - 5 Volt
- 0 - 10 Volt
- 4 - 20 mA
- 0 - 20 mA

PWM-Signale

Frequency outputs: 0 -20 kHz

CAN-connection

Identifier: 2.0B for 11 bit & 29 bit

Data rate: 100 kb - 1 Mb

Scalable to 1 bit



All data subject to technical changes.

IVEKA GmbH

Talweg 8 | 75417 Mühlacker-Lomersheim/Germany

Phone +49 7041 9695-0 | Fax +49 7041 9695-55 | E-Mail info@iveka.de

www.IVEKA.de